

Electronic hygrometer

Temperature range:0°C~50°C 32°F~122°F

Display Resolution:0.1°C; Accuracy:±1°C

Humidity Range:10%RH~95%RH accuracy:60%±5%RH

TA218B: **Temperature and humidity meter, the clock display year, month, day, week**

TA218D: **Temperature and humidity meter, display font larger**

TH218B clock~thermometer~Hygrometer Manual

Functional Overview:

1:Calendar display range:January1,2000~December31,2049; Time display12/24 hour clock.

2:Switch Date/Time/weeks/sec display.

3:memory or remove the maximum/ minimum temperature and humidity

Functional testing: (fitted with battery ,display: January1 ,2004, PM12:00 00°C temperature value)

*:TIME key,time setting,switch display time /date.Hold down the TIME button 2 seconds to enter time settings, and then

TIME button set the corresponding bit will be blinking ,set the following order:12/24 hours , seconds, hours , minutes ,year ,month , day,

*:UP button ,forward button. Press TIME button 2 seconds later, according to the objectives to be set up , transfer press UP key to advance to the set position.

*:MAX/MIN button: Displays the maximum/ minimum temperature humidity recorder in the normal state, according to MAX/MIN key to switch showed the largest→minimum value of the current temperature and humidity. In the MAX or MIN displays status, no buttons automatically after 8 seconds to return the current temperature and humidity display. The maximum / minimum temperature recorded humidity removal,in the MAX or MIN of the state, hold down the MAX/MIN button 2 seconds clear of the show the highest / most low humidity, and return the current temperature and humidity display.

*:°C /°F key:Switch degrees Celsius / Fahrenheit.

FIX the unit on a wall or place on desktop ,product use a 1.5V AAA batteries .Font fuzzy, please replace the battery . And pay attention to environmental protection

TH218D thermometer ~Hygrometer Manual

MAX/MIN button: Display the maximum / minimum

Temperature or remove humidity , the maximum /minimum/temperature humidity records.

In the normal state, according to MAX/MIN key to switch showed the largest、 minimum、 value of the current temperature and humidity. In the MAX or MIN displays status, no buttons automatically after 8 seconds to return the current temperature and humidity display. The maximum/minimum temperature recorded humidity removal, in the MAX or MIN of the state , hold down the MAX/MIN button 2 seconds clear of the show the highest/ most low humidity, and return the current temperature and humidity display.

RESET button : clear reset.

Fix the unit on a wall or place on desktop.

Product use one (1.5V) AAA batteries. Font fuzzy, please replace the battery ,and

Pattention to environmental protection.



MADE IN CHINA